



ATG Electronics® QDriver™ 60W LED Power Supply

USER GUIDE

Part Number HPS-12060-000000-H1
HPS-12060-000000-H2
HPS-24060-000000-H1
HPS-24060-000000-H2



NOTE:

This user guide is to explain the steps necessary to use the specified and assure peak performance. Its intended use is for reference only, by a fully qualified electrician or technician. This document should never be considered a substitute for any provision of a regulation or state and/or local code.

Please read this entire manual to fully understand and safely use this product.

Specifications are subject to change without notice. Please visit www.atgelectronics.com for most recent user guide versions.

GETTING STARTED

ATG Electronics® QDriver™ 60W LED Power Supply is a universal device that operates on input voltage ranging from 85 VAC~264VAC, and provides 5 amperes of filtered and regulated 12VDC power (nominal) or 2.5 amperes of 24VDC power (nominal) to LED lighting fixtures, controllers or decoders etc.

QDriver™ 60W comes with a 1.5 meter (4.92 feet) long power cord with American plug or European plug to suit different interface. It also has a 1.5 meter (4.92 feet) long cable, which can directly attach to ATG Electronics products or via power adaptor board.

QDriver™ 60W is contained in a compact plastic housing and applicable for dry environment.

QDriver™ 60W is the ideal and cost effective solution for driving a small quantity of 12VDC or 24VDC LED lighting fixtures, controllers or decoders etc. It has successfully been installed with thousands of LED lighting systems in the world.

Included in this Box

QDriver™ 60W LED Power Supply, 1 PCs

User Guide, 1 Set

Unpacking

- 1) Unpack and carefully examine the product.
- 2) Report any damage and save all packing materials if any part is damaged during transport.
- 3) Do not attempt to use this apparatus if it is damaged.

ATG
Electronics Corp.

Light your world
Color your life!

Warnings

- 1) Risk of electric shock. Ensure that the power is off when connecting QDriver™ 60W to the lighting device.
- 2) QDriver™ 60W shall be installed and operated by a qualified electrician or technician in accordance relevant local codes.

Cautions

- 1) Suggested continuous working time is around 8 hours, never more than 12 hours.
- 2) Do not use sharp tools near or on the surface of the device.

User Responsibilities

The responsibility of complying with all state and local laws, ordinances, and regulations in regards to the installation, maintenance, and operation of the device lies with the buyer and handler of the device. These parties may include, but are not limited to the contractor, installer, purchaser, owner, and user of the product.

Note:

The instructions and precautions set forth in this user guide are not necessarily all-inclusive, all conceivable, or relevant to all applications as ATG Electronics cannot anticipate all conceivable or unique situations.

PLANNING THE INSTALLATION

This device installation requires planning to ensure timely, successful installation with minimal complications and down time.

Planning Suggestions

Consult an Electrical Inspector to review all wiring plans.

Create a Layout Plan drawing, per a Lighting Designer's or Architect's recommendation.

Consult ATG Electronics Application Engineering Services as needed.

Installation Considerations

When creating your installation plan, consider the following:

- 1) Power of the loads

To increase the reliability, users are suggested to choose a power supply that has a rating of 30% more power than the loads. So when connecting with QDriver™ 60W, the power of the loads is recommended to be around 46W.

- 2) Location of QDriver™ 60W

QDriver™ 60W can ONLY be used for dry environment.

Installing QDriver™ 60W in high-temperature environment must be avoided;

QDriver™ 60W is suggested to be installed in the horizontal positions;

Installation Steps

- 1) Connect QDriver™ 60W to your lighting device;
- 2) Plug QDriver™ 60W into power outlet to light the whole system.

ATG Electronics® QDriver™ 60W LED Power Supply

Input Voltage: 85 VAC~264VAC

Input Frequency : 47 Hz ~63Hz

Output Voltage: 12VDC/24VDC

Output Current: 5A/2.5A

Line regulation (full load): $< \pm 0.5\%$ (full load)

Full load efficiency: $>80\%$

Operating temperature & humidity: $-10^{\circ}\text{C} \sim 50^{\circ}\text{C}$ ($14^{\circ}\text{F} \sim 122^{\circ}\text{F}$), 20% ~ 93%RH(non-condensing)

Storage temperature & humidity : $-20^{\circ}\text{C} \sim +85^{\circ}\text{C}$ ($-4^{\circ}\text{F} \sim 185^{\circ}\text{F}$), 20% ~ 95%RH(non-condensing)

Dimension: L120 * W60 * H40 mm (L4.7 * W2.4 * H1.6 inch)

Weight: 320 g

Work environment: Indoor use, applicable for dry environment

* Detailed specifications please refer to the product catalog of QDriver™ 60W LED Power Supply.

QUALITY WARRANTY

This product is sold pursuant to ATG Electronics Standard Terms and Conditions which can be found at www.atgelectronics.com/warranty and which contain important provisions, including, among others, the Quality Warranty, exclusions and limitations on ATG Electronics liability for damages, and restrictions on available remedial actions.

For any after-sales assistance, please contact our Customer Service Team at service@atgelectronics.com. All your concerns and requests will be handled within 12 hours.

289 Bisheng Road, Suite 4-301, Zhangjiang Hi-Tech Park

Shanghai 201204, CHINA

www.atgelectronics.com

E-mail: sales@atgelectronics.com

Phone: +86-21-33932667

Fax: +86-21-33932677

**ATG
Electronics Corp.**

Light your world
Color your life!